

Portable Amplifier

PR-210 FM/USB

เครื่องช่วยสอนลำโพง 5"

มี FM Radio/USB/SD Card

PROFESSION SPEAKER

PORTABLE AMPLIFIER

PUBLIC ADDRESS SYSTEM



TIS.1195-2536



FM Radio / USB/SD Card

SPECIFICATION : PR-210FM

Input Microphone :	0.60 mV / 4.7 k Ohms.
Auxiliary :	100.mv./100 k Ohms.
Input Digital PlayerMP3 :	USB port/SD card Function
Connector Mic. In :	Phone
Tape in :	RCA.
Input Imp Mic. In :	200 – 20k Ohms.
Tape in :	5k Ohms.
MP3 Player with FM Radio :	
Playing Format :	MP 3
Support :	SD Card & USB
Accept The Capacity :	128 MB to 16 GB
FM Radio :	88.50 MHz.-108.00 MHz.
Frequency Response	150 Hz.-12KHz.
Tone Control	Bass+/- 8 dB at 150Hz. Treble+/- 8 dB at 10 KHz.
Output Impedance	4 Ohms.
Hum and Noise	Less Than -60 dBV.
Power sources	AC.220-240V. 50/60Hz. DC. 12 – 15V. Car Battery.
Weight	2.6 Kg.

คุณสมบัติการใช้งาน PR-210FM

- 2 ช่อง Micไว้สำหรับพูดกระจายเสียง
- 1 ช่อง Auxไว้ป้อนสัญญาณต่าง ๆ
- 1ช่อง FM Radio /USB /SD Card/ MP3
- 2 Tone ปรับได้ทั้ง เสียงทุ้ม-เสียงแหลม
- สามารถใช้ได้ทั้งไฟบ้านAC.220V และไฟในรถยนต์ DC.12V
- ลำโพงขนาด 5 นิ้ว แบบ Fullrange
- ตู้ลำโพงเป็นแบบ Bass Reflex
- ขนาด กxสxล = 185x275x160 มม.
- เหมาะสำหรับใช้เป็นสื่อการเรียนการสอน หรือเรียกอีกอย่างว่า เครื่องช่วยสอน
- ใช้ในการประชาสัมพันธ์ในโรงพยาบาล โรงแรมหรือสถานที่ราชการก็ได้

* Specifications are subject to change without prior notice

